



THE UNIVERSITY *of* EDINBURGH

Edinburgh Research Explorer

A Methodology for Remote Microwave Sterilization Applicable to the Coronavirus and Other Pathogens using Retrodirective Antenna Arrays

Citation for published version:

Kossenas, K, Podilchak, S, Comite, D, Hilario Re, PD, Goussetis, G, Pavuluri, SK, Griffiths, S, Chadwick, R, Guo, C, Bruns, N, Tait-Burkard, C, Haas, JG & Desmulliez, MPY 2021, 'A Methodology for Remote Microwave Sterilization Applicable to the Coronavirus and Other Pathogens using Retrodirective Antenna Arrays', *IEEE Journal of Electromagnetics, RF and Microwaves in Medicine and Biology*, pp. 1-12. <https://doi.org/10.1109/JERM.2021.3077110>

Digital Object Identifier (DOI):

[10.1109/JERM.2021.3077110](https://doi.org/10.1109/JERM.2021.3077110)

Link:

[Link to publication record in Edinburgh Research Explorer](#)

Document Version:

Peer reviewed version

Published In:

IEEE Journal of Electromagnetics, RF and Microwaves in Medicine and Biology

General rights

Copyright for the publications made accessible via the Edinburgh Research Explorer is retained by the author(s) and / or other copyright owners and it is a condition of accessing these publications that users recognise and abide by the legal requirements associated with these rights.

Take down policy

The University of Edinburgh has made every reasonable effort to ensure that Edinburgh Research Explorer content complies with UK legislation. If you believe that the public display of this file breaches copyright please contact openaccess@ed.ac.uk providing details, and we will remove access to the work immediately and investigate your claim.



A Methodology for Remote Microwave Sterilization Applicable to the Coronavirus and Other Pathogens using Retrodirective Antenna Arrays

Konstantinos Kossenas, Symon K. Podilchak, *Member, IEEE*, Davide Comite, *Senior Member, IEEE*, Pascual D. Hilario Re, George Goussetis, *Senior Member, IEEE*, Sumanth K. Pavuluri, Samantha J. Griffiths, Robert J. Chadwick, Chao Guo, Nico Bruns, Christine Tait-Burkard, Jürgen G. Haas, and Marc P.Y. Desmulliez, *Senior Member, IEEE*

Abstract—This paper describes an innovative remote surface sterilization approach applicable to the new coronavirus, severe acute respiratory syndrome coronavirus 2 (SARS-CoV-2). The process is based on the application of a liquid film on the surface or object under sterilization (OUS). A beacon signal is used to self-steer the transmitted power from the designed retrodirective antenna array (RDA) towards the OUS using circularly polarized fields; then, the sterilization is completed by raising and maintaining the required temperature for a certain time. Results suggest that the process takes 5 minutes or less for an angular coverage range over 60° whilst abiding by the relevant safety protocols. This paper also models the power incident onto the OUS, providing consistent results with full-wave simulations. A practical RDA system is developed using a 2x1 microstrip patch array operating at 2.5 GHz and tested through the positioning of a representative target surface. Measurements, developed by sampling the power transmitted by the heterodyne RDA, are reported for various distances and angles, operating in the near-field of the system. To further validate the methodology, an additional experiment investigating virus deactivation through microwave heating was also developed. Measurements have been performed with an open cavity microwave oven on the Coronavirus (strain 229E) and ovalbumin in a cuvette. This demonstrates that the temperature increase of aqueous films up to 60°C by remote microwave-induced heat can denature proteins and deactivate viruses. Possible applications of the method include sterilization of ambulances, medical equipment, and internet of things (IoT) devices.

Keywords—COVID-19, medical devices, microwave heating, near field, retrodirective array, SARS-CoV-2, remote sterilization.

I. INTRODUCTION AND MOTIVATION

THE World Health Organization (WHO) has categorized the severe acute respiratory syndrome coronavirus 2 (SARS-CoV-2) among a family of viruses that can affect animals or humans, causing the COVID-19 disease [1]. The unprecedented situation the entire world is facing with COVID-19 calls for new solutions that help to ensure that medical staff, and the general public, are safe and protected. Understanding the way in which the virus propagates and how the infection occurs is of paramount importance to control the pandemic. When people infected with COVID-19 cough or exhale, droplets are expelled from their nose or mouth and they can diffuse onto objects and surfaces [1]. The virus can survive for hours, or even up to days, on plastic and metallic surfaces [1], which means that people can inadvertently become infected

with COVID-19, becoming potential carriers. These emitted droplets, depending on their size and weight, can also remain suspended in air. The survival of the virus on contaminated surfaces has a vital role in its spreading, therefore sterilization of said surfaces is important to curtail the pandemic.

Accurate information regarding the life-time of the SARS-CoV-2 on infected surfaces is still not completely clear. Based on some early results [1] it is expected to act like other coronaviruses. A preliminary work developed in 2003, when the SARS-CoV-1 was discovered, reported on the stability of coronaviruses in human specimens and related environments. The results made it clear that for at least 96 h SARS was capable of surviving and being infectious in serum, diluted sputum and feces, and up to 72 h for urine. At the same time the virus can remain strongly infectious at low and room temperatures for at least 2 h. Only with the longer exposure in time and at higher temperatures did the virus start to become non-infectious. In addition, ultraviolet C (UVC) irradiation for 9 min has been shown to lead to the elimination of the virus [2].

Recent research has also shown that viruses with pandemic potential, like SARS, have a long survival time on dry surfaces and can infect field settings [3]. Coronaviruses can also survive in water and pre-pasteurized settled sewage, making human exposure possible. Pre-pasteurization refers on the inactivation of the other microorganisms for avoiding the interfere with the cell culture of coronaviruses [4]. Aerosol and surface stability of the new SARS coronavirus has also been recently studied in

K. Kossenas and S.K. Podilchak are with The University of Edinburgh, School of Engineering, Institute of Digital Communication, (corresponding authors: k.kossenas@sms.ed.ac.uk, s.podilchak@ed.ac.uk).

K. Kossenas, S.K. Podilchak, P.D. Hilario Re, G. Goussetis, S.K. Pavuluri, and M.P.Y. Desmulliez are with Heriot-Watt University, Institute of Sensors Signals and Systems, School of Engineering and Physical Sciences (corresponding authors: g.goussetis@hw.ac.uk, m.desmulliez@hw.ac.uk).

D. Comite is with Sapienza University of Rome, Department of Information Engineering, Electronics and Telecommunications (corresponding author: davide.comite@uniroma1.it).

S. J. Griffiths, C. Tait-Burkard, and J. G. Haas are with The University of Edinburgh, Edinburgh Medical School, Infection Medicine (corresponding author: juergen.haas@ed.ac.uk).

N. Bruns, R. J. Chadwick, C. Guo are with University of Strathclyde, Glasgow, Department of Pure and Applied Chemistry (corresponding author: nico.bruns@strath.ac.uk).

[5] using five different materials: copper, cardboard, stainless steel, and plastic. The concentration of the virus (i.e., the titer) was measured at 21°C to 23°C and 40% relative humidity for more than 7 days. The titer of the aerosolized virus was expressed in 50% tissue-culture infectious dose (TCID₅₀) per liter of air. The experiments were repeated three times each. Table I presents the titer results, showing that on cardboard and stainless steel it becomes very low after 24 h. In aerosol form and on copper, the titers require only a few hours to drop to low levels. However, the virus durability on plastic can be very long (up to 48 h) [5].

Abraham and colleagues recently developed guidelines for microwave thermal sterilization in [6]. The authors suggest that a temperature beyond 60°C is required for the thermal destruction of the virus; i.e. SARS-CoV-2, highlighting that the time needed to complete the sterilization is a function of temperature. Specifically, a 3-minute exposure at 75°C is recommended, whereas an exposure of 5 minutes at 65°C and of 20 minutes at 60°C is recommended, adopting a conservative approach on the sterilization time and temperature. Additionally, the Centers for Disease Control and Prevention (CDC) in the United States has published a guideline for disinfection and sterilization methods in health-care facilities, including alcohol, chlorine, and pasteurization [7]. Sterilization can be operated through ionizing and infrared radiation (indicating powers in the order of 600 Watt [8]), which are well-established but are relatively expensive methods, often requiring bulky systems. These features not always match the requirements of health-care facilities (ex. US Food and Drug Administration, FDA) [7]. Microwaves are also regarded as a promising method for sterilization and have a number of applications, which include soft contact lenses, dental instruments, dentures, milk, urinary catheters and many others [7].

The general principle commonly used in a kitchen-based microwave oven can be exploited to produce heat for sterilization [7]. Basically, microwaves can generate friction of the constituent water molecules, usually at 2.45 GHz; typically, an effective microbicide dose requires 60 seconds to 5 minutes, depending on the microorganism being targeted [7]. During radiation, the electric field hits the polar molecules, generating vibrations as well as twisting, turning, and stretching, which causes friction in a viscous environment, thus creating heat. The mechanism is affected by the amount of water present and by the intensity of the incident field [9].

UV radiation is also a natural disinfectant that reduces health-care acquired infections and kills pathogens. It is typically applied to sterilize drinking water and air [10]. There are various factors such as temperature, wavelength, and intensity, which influence the effectiveness of the sterilization process. From a physical viewpoint, UV radiation is associated with wavelengths between 100 and 400 nm, while maximum bactericidal effect takes place at 240 to 280 nm [10]. In health-care environments, UV covers the inactivation of airborne organisms and microorganisms on surfaces [7]. UV can be applied in health-care facilities or emergency vehicles, such as ambulances, which are disinfected by using UV light. Conventional decontamination time can take about 15-20 min

TABLE I
SURVIVAL OF CORONAVIRUS IN AEROSOLS AND ON SURFACES [5].

Titer	Hours of Viability of Virus
Aerosols	< 3
Copper	8
Plastic	72
Cardboard	24
Stainless Steel	< 48

[10].

Research exploring the possibility of eliminating viruses based on a method using confined acoustic vibrations (CAV) was published in [11]. In this approach, energy can be transferred by an incident microwave power density by CAV, which induces stress fractures in the virus structure. This operation has shown to cause deactivation of the airborne virus, whilst being safe for the public. Moreover, an experiment took place to understand the power that was needed for the destruction of the virus, using a horn antenna, with the viral samples being placed below it. The results showed that between 6 to 12 GHz was necessary for the destruction of the viruses with input powers from 0.57 to 3.92 W [11].

We propose here a new methodology and procedure for the remote microwave thermal sterilization of infected surfaces using antennas and electromagnetic (EM) waves at microwave frequencies. The technique is modeled and developed to act against the SARS-CoV-2 causing the COVID-19 disease. The technique can be used in various medical scenarios, such as hospital rooms or ambulances, for contact-less sterilization and virus deactivation. The level of required energy and the possible automation of the system in particular, clearly differentiates the proposed method from other sterilization approaches. For example, only few a Watts are required, offering remote operation with RF beam focusing, not requiring the operator to come in contact with the contaminated surface. In contrast to a more conventional disinfectant spray, this approach is not targeted and focused; i.e., it typically generates a cone of liquid vapour that disperses in air and further requires manual wiping and cleaning by an operator. In fact, a harsh disinfectant would need to be wiped by an operator, which is not always possible or recommended.

The proposed methodology is based on self-steering or retrodirective antenna arrays (RDAs) [12]-[14], which have recently been shown to be advantageous for wireless power transmission systems in the remote charging of batteries within smart phones, tablets, and other devices [15], [16]. There are two basic types of RDAs: passive and active. In the former, the frequencies of the beacon signal and of the re-transmitted signal are typically the same, whereas in active RDAs the two signals can have different frequencies to minimize unwanted electromagnetic coupling. Active RDAs operate by signal heterodyning and are typically referred to as Pon RDAs [12]. Other applications for RDAs include [13], [14] wireless communications, remote sensing, and imaging.

The origin point of the beacon signal can be automatically tracked by the RDA without *a priori* knowledge of its physical position. Therefore, an RDA is capable of transmitting a signal back to the beacon location automatically. The main

concept of our proposed approach is that the object under sterilization (OUS) has a thin water film and a small antenna on it. The antenna generates the radio beacon (see Figs. 1 and 2), allowing the RDA to localize the OUS, to steer its beam towards it, and to start to transfer power wirelessly for remote microwave thermal sterilization and prompt pathogen deactivation.

Existing WiFi transmitters for data communications could be exploited as the beacon signal [15], [16]. This is because the OUS could be medical devices, tablets, and other IoTs, which might connect to conventional wireless local area networks (whose connection is based on beacon signals) within hospitals, ambulances, and other care facilities for example. If needed, small beacon transmitters could be anyway placed on the required surfaces by operators, enabling hands-free sterilization. This can have significant benefits as the radiated beam can be steered automatically towards the contaminated surface, whilst the operator need not to physically touch it. Furthermore, the proposed RDA sterilization approach could be positioned within the walls of ambulances, for example, and in proximity of other indoor facilities making the system completely autonomous. It could also be made handheld for operators with a given steered beam or fixed to be perpendicular (or broadside) to the sterilizing antenna unit which generates EM waves.

The paper is divided into three parts. The first part deals with the theoretical approach and modeling of the problem. Firstly, the microwave thermal sterilization process using a Pon RDA is analytically described modeling a medical device as a rectangular surface, which is then sprayed with a thin film of liquid water. This is treated as the OUS in Section II. The required energy for the sterilization process is examined through simulations and numerical calculations using a commercial full-wave EM solver. As the system operates in the near field (NF), conventional physical quantities, like the radar cross section (RCS) and the power transferred by the RDA are evaluated.

In the second part, the operation of the RDA is simulated and experimentally verified. As outlined in Section III, the OUS is represented by a rectangular surface comprised of two patch antennas operating at two distinct frequencies (2.4 GHz and 2.5 GHz). One acts as the beacon while the other as the effective aperture surface, as required to physically measure the retrodirected high-power signal by the Pon RDA. A parametric analysis has also been developed for some variable distances and angles. The theoretical results of the first section are then compared with simulations and measurements. The power radiated at 2.4 GHz is set at a level capable of achieving the required temperature to start the sterilization, abiding by the relevant international safety protocols.

In the third part, virus inactivation was investigated using an open-end microwave cavity as described in [17]. To experimentally study the inactivation, the human coronavirus strain 229E with a green fluorescent protein (GFP) tag (CoV-229E-GFP) was used [18]. The virus was diluted to a multiplicity of infection (MOI) of 0.3 in serum-free Dulbecco's modified Eagle's medium (DMEM), and 200 μ l transferred to a cuvette. After microwave exposure, residual infectivity was determined




Fig. 1. System overview of an RDA operating as a remote microwave thermal sterilizer. The beacon signal transmitter allows for localizing the OUS and the RDA re-radiates power towards that direction.

by infection of virus-susceptible Huh7 cells and measurement of the replication growth curves. Results are presented in Section IV. Finally, it is demonstrated that microwave induced heating of liquid films to 60°C with an open end microwave cavity can lead to protein denaturation, as visually observed for a solution of egg white, and to deactivation of the CoV-229E-GFP strain, as demonstrated by the aforementioned experiment. A short discussion and conclusion follows.

II. MICROWAVE THERMAL STERILIZATION TECHNIQUE

This section describes the microwave thermal sterilization technique of the OUS by using an RDA and the beacon signal. Classic thermodynamic theory, in combination with conventional wireless power transfer (WPT) and radar techniques, are considered. A test case with an RDA radiating towards a rectangular plate, sprayed with a water layer (assumed as the OUS), from different distances and angles is described. A numerical model of the time required to start the microwave thermal sterilization is developed.

A. Description of the Microwave Thermal Sterilization System

The system is illustrated in Fig. 1, where the RDA system emits the desired level of microwave power needed to start the microwave thermal sterilization.

The microwave thermal sterilization process is detailed in Fig. 2: a) the contaminated heart rate monitor (or any generic medical device, equipment, etc.) is covered by a liquid film at room temperature (25°C), b) the medical device sends the beacon radio signal through a small integrated antenna, c) the RDA receives it and, because of the phase conjugation mechanism made possible by the Pon heterodyne circuit system [12], it steers and radiates power back towards the medical device for a certain temporal interval. As discussed in [6], the virus is deactivated at a minimum temperature of 60° C. The required amount of power and time needed for the liquid film to reach 60° C are discussed in the following.

Given the electrically large aperture size for the RDA required to achieve the desired incident power on the OUS positioned at a distance r and the relevant path losses, it is expected that the RDA should operate in the NF. The boundary between the NF and the far-field (FF) operation is conventionally approximated by $r = \frac{2D^2}{\lambda}$, where D is the maximum




Fig. 2. Illustration of the microwave thermal sterilization process for a medical device where a liquid film has been applied on it: (a) The medical device sends a beacon signal towards the RDA, (b) RDA receives the beacon signal and starts to transmit power towards the medical device, (c) the required temperature of the liquid film has been achieved, and (d) the microwave thermal sterilization has been completed.




Fig. 3. Orientation of the RDA with respect to a rectangular plate (OUS). The beacon signal transmitter allows for localizing the OUS and the RDA transmits power in the NF by an antenna array made by N_t elements towards that direction.

linear dimension of the antenna and λ is the wavelength in free-space [19]. Given the RDA transmitted power (i.e., P_t) and its gain (i.e., G_t), it is possible to calculate the power impinging on the OUS. Indicating with θ and ϕ , the elevation incidence angle and the azimuthal incidence angle towards the RDA (Fig. 3), the incident power is given by

$$P_i = \frac{P_t G_t(\theta, \phi)}{4\pi r^2} \sigma(\theta, \phi), \quad (1)$$

where σ is the target radar cross section (RCS) [20], [21].

As a test case, we consider here a flat rectangular plate OUS with dimensions α , b . The coordinates of the source position are $(r \cos\phi \sin\theta, r \sin\phi \sin\theta, r \cos\theta)$ where $r = \|\mathbf{r}\|$. A simple formula for the RCS of a rectangular plate in the NF is given

in the following [22]:

$$\sigma_{\text{plate}}(\theta, \phi) = \frac{\pi r^2 \cos^2 \theta}{4(1-c^2)(1-s^2)} \left| F_{1c} F_{1s} + \frac{3c^2}{1-c^2} F_{1s} (F_{1c} + E_{1c}) + \frac{3s^2}{1-s^2} F_{1c} (F_{1s} + E_{1s}) \right|^2. \quad (2)$$

where the Fresnel integral is defined as $F(x) = \int_0^x e^{\frac{j\pi t^2}{2}} dt$ and the following definitions holds: $c = \sin\theta \cos\phi$, $s = \sin\theta \sin\phi$. On this basis, the F_{1c} , F_{1s} , E_{1c} and E_{1s} functions are given by

$$\begin{cases} F_{1c} = F(u_c + v_c) + F(u_c - v_c) \\ F_{1s} = F(u_s + v_s) + F(u_s - v_s) \end{cases} \quad (3)$$

$$\begin{cases} E_{1c} = \frac{1}{j\pi v_c} \left[e^{\frac{j\pi(u_c - v_c)^2}{2}} - e^{\frac{j\pi(u_c + v_c)^2}{2}} \right] \\ E_{1s} = \frac{1}{j\pi v_s} \left[e^{\frac{j\pi(u_s - v_s)^2}{2}} - e^{\frac{j\pi(u_s + v_s)^2}{2}} \right] \end{cases} \quad (4)$$

where

$$\begin{cases} u_c \pm v_c = \sqrt{\frac{r}{\lambda(1-c^2)}} \left[\frac{\alpha(1-c^2)}{r} \pm 2c \right] \\ u_s \pm v_s = \sqrt{\frac{r}{\lambda(1-s^2)}} \left[\frac{b(1-s^2)}{r} \pm 2s \right] \end{cases} \quad (5)$$

B. Simulation of the Radiated Power

We evaluate here the incident power given by (1) performing a simulation. The RDA system is composed of a two-element array operating at 2.5 GHz with input power $P_t = 1$ W (3 W also considered for comparison); a rectangular water layer (i.e., the OUS) with dimensions $\alpha = 14$ cm, $b = 8$ cm, thickness $t = 0.25$ mm is included in the simulation. The OUS is rotating from -90° to 90° along the azimuthal angle (ϕ), keeping constant the elevation angle (θ). In each rotation the RDA beam was steered towards the OUS direction and the power incident on it was recorded, evaluating the antenna gain ($G_t(0, \phi)$) is at the relevant direction (1). The plots in Fig. 4 show the results for two different distances, for $r = 10$ cm and $r = 25$ cm; in both cases the RDA operates within the NF.

C. Required Energy for Microwave Thermal Sterilization

The microwave thermal sterilization of an object requires to control the involved physical parameters, such as the required thermal energy, the temporal duration, and the dimensions of the surface under sterilization. An object with a given mass and heat capacity can be described with the specific heat c_p [23], defined as the ratio between mass and capacity [24]. Thus, the energy stored by the substance can be calculated as $E = c_p \Delta T m$ [25], where E is the required heat energy for increasing the temperature of the substance. ΔT is the differential temperature between the initial and the final states of the substance and m is the mass of the substance, which can be expressed in terms of the volume (V) and the density (ρ) of the substance as $m = V \rho$ [26]. Assuming that a source transfers thermal energy, the difference in temperature of the




Fig. 4. Incident power generated by a 2×1 RDA, for two different input power (i.e., 1 W and 3 W); upon on a rectangular water-based aperture considering distances (a) $r = 10$ cm and (b) $r = 25$ cm.

substance is equal to ΔT . In a time interval t_{total} , therefore, the needed power is given by $P = E/t_{\text{total}}$ [27].

Combining (1) with the aforementioned basic energy equations a numerical model of the time needed to increase the temperature is developed. Given the OUS volume, density and heat capacity, the original and desired final temperature, RCS, RDA gain as well as the distance between the two devices, the following expression can retrieved:

$$t_{\text{total}} = \frac{4\pi r^2}{P_t} \frac{c_p \Delta T V \rho}{\sigma(\theta, \phi) G_t(\theta, \phi)}. \quad (6)$$

The formula in (6) is considered here to evaluate the performance of the system constituted by a 2×1 RDA and the rectangular water layer. The desired temperature was set to 60°C , whilst the original temperature was assumed equal to 25°C . The specific heat capacity of water is $c_p = 4179.6 \text{ J kg}^{-1} \text{ K}^{-1}$, its density is $\rho = 10^3 \text{ Kg/m}^3$, and its volume is $V = \alpha b t \text{ m}^3$ [28]. Fig. 5 presents the total time needed for the sterilization of water in terms of various distances and azimuthal angles with respect to the RDA, setting a transmitted power $P_t = 1$ W and 3 W. The results in Fig. 5 demonstrate that the azimuthal angles between the RDA and the OUS required to reach the desired temperature to start the microwave thermal sterilization has a significant impact on the time. As expected, the minimum value is achieved at broadside, (i. e., $\theta = 0^\circ$). This is because the antenna gain decreases off broadside, highlighting the importance of the self-steering RDA. It should be mentioned that higher input power (P_t) and directivity can help to reduce the sterilization time.

In order to validate the formula in (6) the time required for raising the temperature by 1°C was assessed through a simple experimental setup. This included a single-element patch antenna (linearly polarized) operating at 2.5 GHz and a rectangular aluminium ($\alpha \times \alpha$) target covered by a water layer ($t \approx 0.5$ cm), placed within an anechoic chamber (Fig. 6).




Fig. 5. Required time to heat the water film to 60°C to induce the sterilization of the coronavirus. Water layer aperture as in Fig. 4. For $\pm 30^\circ$ azimuthal angles the time is less than 5 minutes, for an input power of 3 W. It is expected that with increased levels of power, sterilization time can decrease.




Fig. 6. Experimental setup: the relative position between target and the single-element patch antenna was set to 10 cm; incident angle equal to 0° .

A signal generator (Keysight MXG N5183B) was used with output power equal to -15 dBm, connected in series with a 30-dB power amplifier (MiniCircuits ZFL-2500+) so that the input power at the antenna was $P_t = 15$ dBm (i.e., ≈ 0.03 W). The relative distance between the antenna and the target was set to 10 cm and the incident angle at 0° . Based on these values and the estimated required time for the changing of temperature by 1°C is about 3.5 h. The original temperature of the target was measured to be 20.3°C through a digital laser temperature gun. After 3.5 h the measured temperature was 21.4°C . The temperature around the water layer was also monitored with a digital thermometer equipped by a probe; this temperature was 18.6°C at the beginning of the experiment and 19.4°C at the final target temperature recording and these results are consistent with (6).




Fig. 7. Measured received power at different distances from the RDA (broadside) in comparison with the theoretical expected power using the free-space path loss model (FSPL) and the indoor propagation ITU model [31]. The arrays for the dual-pol Pon RDA prototype (using CP antenna elements) are shown in the inset. RF components: including mixers (1), amplifiers (2 and 3), power divider (4) and voltage control oscillator (5). CP antenna elements are employed to provide orientation flexibility for the OUS and the RDA.

III. NEAR-FIELD RDA

A. Pon-based RDA Design and Operation

The Pon RDA is a heterodyne system that avoids the use of circulators since the transmit and receive arrays are isolated; the structure uses RF mixers to provide retrodirectivity by phase conjugation [14]. This principle is simple and well established, it exploits the product between two input signal tones [12], which constitutes the RF input signal and the local oscillator signal (LO). Gain blocks (namely, amplifiers) are typically employed to boost the retrodirected power. The Pon RDA designed in this work follows [15] and collects the beacon signal with a receiving array (with one polarization) and it retrodirects the radiation back to the OUS with a high-power transmitting array with another polarization. The radiating element in this RDA architecture is a two-element circularly polarized (CP) patch array. CP operation is needed to avoid potential polarization mismatches between the target and the RDA while also allowing for orientation free movement of the OUS. Element decoupling strategies were not considered for simplicity in our work, as element coupling values were -20 dB or less. Different approaches, such as in [29], [30], can be adapted to our design if better performance is needed.

To test the performance of the RDA system in the NF, an RDA system with lower gain and reduced cost when compared to [15], was designed with FR-4 material constituting a simple demonstrator as shown in Fig. 7 (see inset). The tracking plane is perpendicular to the RDA aperture containing the two-element arrays. Thus, each RF chain is defined by a receiving CP antenna element, a mixer (Linear Technology), a driver amplifier from (MiniCircuits ZFL-2500+), a power amplifier (TriQuint TQP9111), and a CP transmitting antenna.

Considering a two-element Pon-RDA, the received beacon signal at the antenna elements (i.e., f_{RX}) goes directly into the RF port of each mixer. It should be mentioned that all mixers share a common LO to ensure consistent reference. The output signal is then phase conjugated [12], thus an inverted




Fig. 8. Monostatic measurements for various ranges; i.e. RDA to the OUS.




Fig. 9. Bistatic measurements in the NF at different angles and distances for the proposed RDA: (a) 0°, (b) -30°, (c) -15°, (d) 15° and (e) 30°.

progressive phase difference between antenna elements is achieved, resulting in a wavefront (f_{TX}) propagating towards the same direction as the beacon signal generated by the OUS. This process occurs in real-time, thereby performing analog signal processing [32].

The power received at broadside and at different distances from the OUS has been measured as shown in Fig. 7. The following NF expression for the path loss is considered [33]:

$$P(r, f) = \frac{G_{TX}G_{RX}}{4} \left(\frac{1}{(kr)^2} - \frac{1}{(kr)^4} + \frac{1}{(kr)^6} \right), \quad (7)$$

where G_{TX} is the gain of the transmitter, G_{RX} is the gain in reception, k is the free-space wavenumber. The measured received power well approximates the trend for the free-space path loss model (Fig. 7). However, there is poor agreement with the indoor propagation model after about 1 m [31] which takes into consideration multipath effects. Such disagreement is justified in the fact that the measurements were made inside an anechoic chamber, replicating a free-space environment.




Fig. 10. Bistatic measurements (circles) and simulations (cont. lines) for different ranges and angles: (a) 10 cm and (b) 25 cm, (i) -20° , (ii) 0° and (iii) 20° .

Monostatic and bistatic measurements were completed for proof of concept (see Figs. 8 to 10). The procedure to acquire monostatic and bistatic patterns is illustrated in Fig. 7 of [15]. The bistatic pattern corresponds to the radiation pattern of the RDA when the beacon tone is set at a given angle. To test the tracking capabilities of the RDA, several bistatic patterns at different angular positions of the beacon signal are considered. The transmit signal of the OUS, i.e., the beacon, is kept at a given angle, while the receiver patch (which samples the field) rotates around to map the complete beam pattern for a given angular range. Therefore it is expected that the RDA will be continuously pointing and tracking its maximum back towards the beacon OUS.

Results of the monostatic measurements can be found in Fig. 8. A comparison of the normalized received power of the patch antenna for a range from -50° to 50° and of various distances from NF to FF is presented. The boundary in this case is at 35 cm. Respectively, results of the bistatic measurements can be found in Fig. 9. Comparison of the normalized received power for a range from -50° to 50° and of various distances from NF to FF, as well, for five given angles θ : 0° , (b) -30° , (c) -15° , (d) 15° and (e) 30° .

Bistatic measurements at 10 cm and 25 cm have also been made and compared in this case to the simulations in Fig. 10. In Fig. 10(a) it can be observed that measurements and simulations have a similar field pattern. Despite the difficulties to make the measurements with high accuracy (the mechanical supports were very close together for the RDA and patch receiver), the shape of the measured points follows the expected trend. On the other hand, in Fig. 10(b), the measured points match very well to that of the expected pattern shape, also demonstrating that the required NF tracking is possible.

B. Health and Safety Discussion

The International Commission on Non-Ionizing Radiation Protection (ICNIRP) has set limitations on exposure to elec-

TABLE II
ELECTROMAGNETIC FIELD EXPOSURE RESTRICTIONS LIMITS, BASED ON ICNIR, FROM 100 100 kHz TO 300 GHz [34].

Exposure scenario	Whole-body av. SAR W/Kg	Local Head/Torso SAR W/Kg	Local Limb SAR W/Kg
Occupational	0.4	10	20
General Public	0.08	2	4

tromagnetic fields. There are two exposure scenarios, one for the occupational and one for the general public. Those two have different limits, in three categories. The first one refers to the whole body exposure and the others to the local head/torso and the local limb exposures, respectively. There are a number of different ways the exposure can be measured, the most common being the specific energy absorption rate (SAR, W/Kg). Table II shows the exposure limits for the five aforementioned categories, from 100 kHz to 6 GHz. The restrictions refer to average intervals of 30 min in terms of the whole-body average SAR and 6 min for the local SAR [34].

IV. VIRUS DEACTIVATION THROUGH MICROWAVE RADIATION EXPERIMENTS

The section describes the microwave heat experiment for coronavirus strain CoV-229E-GFP deactivation. The experiment demonstrated the protein denaturation and coronavirus deactivation, using a microwave open ended cavity system, which induced microwave heating of aqueous films.

A. Inactivation of the Virus

The microwave open ended cavity system used for the heat experiments was originally developed to enable rapid bonding of individual microelectronic components on a board assembly [17], [35], [36]. This system has an advantage of volumetric and uniform heating, selective energy deposition with reduced processing times and increased energy efficiency. Microwave heating was achieved using this open-ended single mode resonant microwave applicator/oven which has been described in [35]. Test specimens consist of 200 μ l of Cov-229E-GFP diluted to a multiplicity of infection (MOI) of 0.3 in DMEM, in a cuvette of internal volume 8 mm \times 8 mm \times 8 mm. The samples were then heated at a constant ramp up rate of 1.5°C/s to the chosen inactivation temperature (50, 60, 70 and 100°C) held for varying amounts of time (10 seconds to 60 seconds). Residual virus infectivity was determined by infection of virus-susceptible Huh7 cells and measurement of virus replication growth curves as a function of GFP fluorescence was recorded.

Fig. 11 shows the set and measured temperature profiles and net input power for a 70°C temperature cycle with 60 seconds set hold time. The net input microwave energy for this temperature cycle is 164 Joules, approximately. Fig. 12 indicates the survival rates of virus at various temperatures and exposure durations. It can be seen that the virus survival decreases with both time and temperature with a maximum of 30% virus death at 60°C , and 100% virus death following exposure to 70°C for 30 s.




Fig. 11. Net microwave power along with the temperature profile for a 70°C heating cycle experiment with the virus suspension for 60 second hold time period.




Fig. 12. Survival rates of virus when exposed to the microwaves in an open ended microwave cavity for 10-60 seconds at four different temperatures: 50, 60, 70 and 100°C.

B. Visual Thermal Assay based on Protein Denaturation

In order to demonstrate that microwave-induced heating of aqueous films can lead to protein denaturation and virus deactivation, an open microwave cavity as described above is used to irradiate protein solution (1:1 mixture of hen egg white and phosphate buffered saline (PBS) at pH 7.4). The protein solution was monitored for 3 minutes where there was an obvious colour change from colourless to white. The transparent solution turns white opaque upon irradiation, therefore giving a direct visual indication that the protein denatured and gelled. Hen egg white proteins are known to denature at 60°C [37]. This was also confirmed by another controlled experiment in which the egg white/PBS solution was thermally heated to 60°C. To this end, approximately 500 μ l of the solution was pipetted onto a glass microscope slide. A second slide was placed on top of the solution to minimise loss of solution by evaporation. This was then placed on a variable temperature hotplate set to 60°C. This experiment was repeated with the open ended cavity system with a heating ramp up from 25 to 60°C at 1°C/s and a hold time of 60 seconds. In this second experiment, the solution was monitored for 2 minutes where there was an obvious colour change from colourless to white (Fig. 13) similar to the hotplate experiment.

While these three sets of experiments show that microwave




Fig. 13. Microwave heated protein solution result to 60°C by microwave irradiation. (a) Colourless solution before being thermally heated. (b) White solution after thermal heating. The white colour in the solution shows that the protein has been denatured and gelled.

irradiation of thin aqueous films to above 60°C can lead to protein denaturation and virus deactivation, it has to be emphasized that these experiments were done with a simpler microwave set-up as the one outlined in this publication, because the current RDA prototype does not yet have a powerful enough power source and beam directivity to deliver the required radiation intensities. Nevertheless, the experiments show that microwave heating to a modest 60°C is sufficient to achieve the desired damage to proteins and to viruses, and therefore to sterilize surfaces demonstrating proof-of-concept for the proposed methodology and approach for remote microwave sterilization. Two videos can also be found in the supplementary information about the hotplate and microwave cavity denature of egg white.

V. CONCLUSION

A sterilization method applicable against the new coronavirus has been presented in this paper. The technique requires a small transmitter suitably positioned on the OUS to provide its location. The RDA receives the transmitted beacon signal and transmits power to the OUS until it reaches the desired temperature. A study has been done to test the tracking capabilities of the Pon RDA in the NF.

A liquid film water was considered to produce heat for sterilization and the amount of power needed to deactivate the coronavirus was calculated. More specifically, the total time needed to reach 60°C. The studied liquid film has dimensions $a = 14$ cm, $b = 8$ cm and thickness $t = 0.25$ mm, whilst the total input power of the RDA is 3 W, maintaining below the exposure limits. The results showed that the study can be feasible for an azimuthal angle range from -40° to 40° and a distance $r = 10$ cm. For $r = 25$ cm the range reduced from -20° to 20° . At the best case scenario (i.e., an OUS placed at broadside and $r = 10$ cm) less than 4 min were needed to complete the heating and the sterilization process. Better performances can be achieved indeed by increases the power of the transmitter or increasing the aperture size of the RDA. Experiments have also been conducted to demonstrate that microwave-induced heating of aqueous films can lead to protein denaturation and virus deactivation. Measurements from these experiments show that the deactivation of viruses due to microwave induced heat is possible above 60°C and can be achieved with $< 99.9\%$ certainty at 70°C above 20 seconds.

ACKNOWLEDGMENT

Authors would like to acknowledge the financial support of the Engineering & Physical Research Science (EP-SRC) funding agency through the platform grant Multi-Modal Manufacturing of Medical Devices (4mD) under the grant number EP/P027415/1, the Biotechnology and Biological Sciences Research Council Institute Strategic Program grant funding to The Roslin Institute (BBS/E/D/20241866, BBS/E/D/20002172, and BBS/E/D/20002174). Also J.G. Haas is funded by BBSRC BB/T003138/1, MRC MR/P011349/1 and IMI2 CARE.

REFERENCES

- [1] WHO. (2020) Coronavirus disease (covid-19) pandemic. [Online]. Available: <https://www.who.int/emergencies/diseases/novel-coronavirus-2019>
- [2] C. S. Heilingloh, U. W. Aufderhorst, L. Schipper, U. Dittmer, O. Witzke, D. Yang, X. Zheng, K. Sutter, M. Trilling, M. Alt, E. Steinmann, and A. Krawczyk, "Susceptibility of sars-cov-2 to uv irradiation," *American Journal of Infection Control*, vol. 48, no. 10, pp. 1273–1275, 2020. [Online]. Available: <https://www.sciencedirect.com/science/article/pii/S0196655320307562>
- [3] J. Otter, C. Donskey, S. Yezli, S. Douthwaite, S. Goldenberg, and D. Weber, "Transmission of sars and mers coronaviruses and influenza virus in healthcare settings: The possible role of dry surface contamination," *Journal of Hospital Infection*, vol. 92, 10 2015.
- [4] L. Casanova, W. Rutala, D. Weber, and M. Sobsey, "Survival of surrogate coronaviruses in water," *Water research*, vol. 43, pp. 1893–8, 02 2009.
- [5] N. van Doremalen, T. Bushmaker, D. Morris, M. Holbrook, A. Gamble, B. Williamson, A. Tamin, J. Harcourt, N. Thornburg, S. Gerber, J. Lloyd-Smith, E. Wit, and V. Munster, "Aerosol and surface stability of sars-cov-2 as compared with sars-cov-1," *New England Journal of Medicine*, vol. 382, 03 2020.
- [6] J. Abraham, B. Plourde, and L. Cheng, "Using heat to kill sars-cov-2," *Reviews in Medical Virology*, vol. 30, p. e2115, 07 2020.
- [7] R. A. William, D. J. Weber, and the Healthcare Infection Control Practices Advisory Committee (HICPAC). (2008) Guideline for disinfection and sterilization in healthcare facilities. [Online]. Available: <https://www.cdc.gov/infectioncontrol/guidelines/disinfection/>
- [8] V. Mata-Portuguez, L. Sanchez, and E. Acosta-Gio, "Sterilization of heat-resistant instruments with infrared radiation," *Infection control and hospital epidemiology: the official journal of the Society of Hospital Epidemiologists of America*, vol. 23, pp. 393–6, 07 2002.
- [9] S. American. (2008) How the microwave works. [Online]. Available: <https://www.scientificamerican.com/article/how-the-microwave-works/>
- [10] Frazer. (2020) Disinfecting ems vehicles with ultraviolet light. [Online]. Available: <https://www.frazerbilt.com/blog-ambulance-disinfection-system/>
- [11] S. C. Yang, H. C. Lin, T. M. Liu, J. T. Lu, W. T. Hung, Y. R. Huang, Y. C. Tsai, C. L. Kao, S. Y. Chen, and C. K. Sun, "Efficient structure resonance energy transfer from microwaves to confined acoustic vibrations in viruses," *Scientific Reports*, vol. 5, p. 18030, 12 2015.
- [12] C. Pon, "Retrodirective array using the heterodyne technique," *IEEE Transactions on Antennas and Propagation*, vol. 12, no. 2, pp. 176–180, 1964.
- [13] R. Y. Miyamoto and T. Itoh, "Retrodirective arrays for wireless communications," *IEEE Microwave Magazine*, vol. 3, no. 1, pp. 71–79, 2002.
- [14] V. Fusco and N. Buchanan, "Developments in retrodirective array technology," *IET Microwaves, Antennas Propagation*, vol. 7, no. 2, pp. 131–140, 2013.
- [15] P. D. Hilario Re, S. K. Podilchak, S. A. Rotenberg, G. Goussetis, and J. Lee, "Circularly polarized retrodirective antenna array for wireless power transmission," *IEEE Transactions on Antennas and Propagation*, vol. 68, no. 4, pp. 2743–2752, 2020.
- [16] S. A. Rotenberg, S. K. Podilchak, P. D. H. Re, C. Mateo-Segura, G. Goussetis, and J. Lee, "Efficient rectifier for wireless power transmission systems," *IEEE Transactions on Microwave Theory and Techniques*, vol. 68, no. 5, pp. 1921–1932, 2020.
- [17] S. Pavuluri, M. Ferenets, G. Goussetis, M. Desmulliez, T. Tilford, R. Adamietz, G. Mueller, F. Eicher, and C. Bailey, "Encapsulation of microelectronic components using open-ended microwave oven," *Components, Packaging and Manufacturing Technology, IEEE Transactions on*, vol. 2, pp. 799–806, 05 2012.
- [18] L. e. a. Cervantes-Barragan, "Dendritic cell-specific antigen delivery by coronavirus vaccine vectors induces long-lasting protective antiviral and antitumor immunity," *mBio*, 09 2010.
- [19] C. Balanis, *Antenna Theory: Analysis and Design*. Wiley, 2012. [Online]. Available: <https://books.google.co.uk/books?id=vIPSZ48DnuEC>
- [20] S. Khang, D. Lee, I. Hwang, T. Yeo, and J. Yu, "Microwave power transfer with optimal number of rectenna arrays for midrange applications," *IEEE Antennas and Wireless Propagation Letters*, vol. 17, no. 1, pp. 155–159, 2018.
- [21] E. Yavari, O. Boric-Lubecke, and S. Yamada, *Radar Principles*. John Wiley & Sons, Ltd, 2016, ch. 2, pp. 21–38. [Online]. Available: <https://onlinelibrary.wiley.com/doi/abs/10.1002/9781119078418.ch2>
- [22] C. Bourlier and P. Pouliguen, "Useful analytical formulae for near-field monostatic radar cross section under the physical optics: Far-field criterion," *IEEE Transactions on Antennas and Propagation*, vol. 57, no. 1, pp. 205–214, 2009.
- [23] G. H. Rooij, "Methods of soil analysis. part 4. physical methods," *Vadose Zone Journal*, vol. 3, pp. 722–723, 2004.
- [24] J. Khachan, "Heat capacity, specific heat, and heat of transformation," in *Thermal Properties of Matter*, ser. 2053-2571. Morgan & Claypool Publishers, 2018, pp. 4–1 to 4–8. [Online]. Available: <http://dx.doi.org/10.1088/978-1-6817-4585-5ch4>
- [25] I. B. of Weights and Measures. (2006) The international system of units (si). [Online]. Available: https://www.bipm.org/utis/common/pdf/si_brochure_8_en.pdf
- [26] T. E. of Encyclopaedia Britannica. (2020) Density. [Online]. Available: <https://www.britannica.com/science/density>
- [27] ——. (2020) Power. [Online]. Available: <https://www.britannica.com/science/power-physics>
- [28] ——. (2020) Water. [Online]. Available: <https://www.britannica.com/science/water>
- [29] M. Alibakhshikenari, F. Babaeian, B. S. Virdee, S. Aissa, L. Azpilicueta, C. H. See, A. A. Althuwayb, I. Huynen, R. A. Abd-Alhameed, F. Falcone, and E. Limiti, "A comprehensive survey on "various decoupling mechanisms with focus on metamaterial and metasurface principles applicable to sar and mimo antenna systems"," *IEEE Access*, vol. 8, pp. 192 965–193 004, 2020.
- [30] M. Alibakhshikenari, B. Virdee, P. Shukla, C. See, R. Abd-Alhameed, M. Khalily, F. Falcone, E. Limiti, K. Ouazzane, and N. Ojaroudi Parchin, "Isolation enhancement of densely packed array antennas with periodic mtm-photonic bandgap for sar and mimo systems," *IET Microwaves, Antennas & Propagation*, 03 2019.
- [31] "Propagation data and prediction methods for the planning of indoor radiocommunication systems and radio local area networks in the frequency range 900 mhz to 100 ghz," 1997.
- [32] S. L. Karode and V. F. Fusco, "Near field focusing properties of an integrated retrodirective antenna," in *IEE National Conference on Antennas and Propagation*, 1999, pp. 45–48.
- [33] H. G. Schantz, "Near field propagation law a novel fundamental limit to antenna gain versus size," in *2005 IEEE Antennas and Propagation Society International Symposium*, vol. 3A, 2005, pp. 237–240 vol. 3A.
- [34] I. C. on Non-Ionizing Radiation Protection (ICNIRP). (2020) Guidelines for limiting exposure to electromagnetic fields (100 khz to 300 ghz). [Online]. Available: <https://www.icnirp.org/cms/upload/publications/ICNIRPrfgdl2020.pdf>
- [35] S. Pavuluri, M. Desmulliez, G. Goussetis, V. Arrighi, K. Johnston, R. Adamietz, T. Tilford, and C. Bailey, "Post cure behaviour of encapsulants for qfn packages processed by an open-ended single mode resonant microwave applicator," *2011 IEEE 13th Electronics Packaging Technology Conference, EPTC 2011*, pp. 573–578, 12 2011.
- [36] K. Johnston, S. Pavuluri, M. Leonard, M. Desmulliez, and V. Arrighi, "Microwave and thermal curing of an epoxy resin for microelectronic applications," *Thermochimica Acta*, vol. 616, pp. 100–109, 08 2015.
- [37] Y. Mine, T. Noutomi, and N. Haga, "Thermally induced changes in egg white proteins," *Journal of Agricultural and Food Chemistry*, vol. 38, no. 12, pp. 2122–2125, 1990.



Konstantinos Kossenias was born in Chios, Greece, in 1993. He received Diploma of Electrical & Computer Engineering (Integrated BSEE & MSEE) from Aristotle University of Thessaloniki, Thessaloniki, Greece, in 2017. He is currently pursuing the Ph.D. degree with University of Edinburgh (UoE), Edinburgh and the Heriot-Watt University (HWU), Edinburgh.

His research interests include the analysis and design of microwave and antenna technologies.




Symon K. Podilchak (S'03-M'05) received the B.A.Sc. degree in Engineering Science from the University of Toronto, Toronto, ON, Canada, in 2005, the M.A.Sc. and Ph.D. degrees in Electrical Engineering from Queen's University, Kingston, in 2008 and 2013, respectively, where he received the Outstanding Dissertation Award for his Ph.D.

From 2013 to 2015, he was an Assistant Professor with Queen's University. In 2015, he joined Heriot-Watt University, Edinburgh, U.K., as an Assistant Professor, and became an Associate Professor in

2017. He is currently a Senior Lecturer with the School of Engineering, The University of Edinburgh, Edinburgh.

He is also a registered Professional Engineer (P.Eng.) and has had industrial experience as a computer programmer, and has designed 24 and 77 GHz automotive radar systems with Samsung and Magna Electronics. Recent industry experience also includes the design of high frequency surface-wave radar systems, professional software design and implementation for measurements in anechoic chambers for the Canadian Department of National Defence and the SLOWPOKE Nuclear Reactor Facility. He has also designed compact antennas for wideband military communications, highly compact circularly polarized antennas for CubeSats with COM DEV International and The European Space Agency (ESA), and, new wireless power transmission systems for Samsung. His research interests include surface waves, leaky-wave antennas, metasurfaces, UWB antennas, phased arrays, and RF integrated circuits.

Dr. Podilchak and his students have been the recipient of many best paper awards and scholarships; most notably Research Fellowships from the IEEE Antennas and Propagation Society (AP-S), the IEEE Microwave Theory and Techniques Society (MTT-S), and the European Microwave Association. He also received a Postgraduate Fellowship from the Natural Sciences and Engineering Research Council of Canada (NSERC) and five Young Scientist Awards from the International Union of Radio Science (URSI). In 2011, 2013 and 2020, student paper awards were received at the IEEE International Symposium on Antennas and Propagation, and in 2012, the Best Paper Prize for Antenna Design at the European Conference on Antennas and Propagation for his work on CubeSat antennas, and in 2016, he received the European Microwave Prize for his research on surface waves and leaky-wave antennas. In 2017 and 2019, he was bestowed a Visiting Professorship Award at Sapienza University, Rome, Italy, and from 2016 to 2019 his research was supported by a H2020 Marie Skłodowska-Curie European Research Fellowship. He was recognized as an Outstanding Reviewer for the IEEE TRANSACTIONS ON ANTENNAS AND PROPAGATION in 2014 and 2020. He was also the Founder and First Chairman of IEEE AP-S and IEEE MTT-S Joint Chapters in Canada and Scotland. In recognition of these services, he was presented with an Outstanding Volunteer Award from IEEE. He has been a Lecturer for the European School of Antennas and an Associate Editor for IET Electronics Letters. Currently he serves as a Guest Associate Editor for IEEE Open Journal of Antennas and Propagation and IEEE Antennas and Wireless Propagation Letters.



Davide Comite (Senior Member, IEEE) received the master's degree (cum laude) in telecommunications engineering and the Ph.D. degree in electromagnetics and mathematical models for engineering from the Sapienza University of Rome, Rome, Italy, in 2011 and 2015, respectively. He is currently a Postdoctoral Researcher with the Sapienza University of Rome. He was a Visiting Ph.D. Student with the Institute of Electronics and Telecommunications of Rennes, University of Rennes 1, France, from March to June 2014, and a Postdoctoral Researcher with

the Center of Advanced Communications, Villanova University, PA, USA, in 2015.

His scientific interests include the study and design of leaky-wave antennas, 2-D periodic leaky-wave antennas, and the generation of non-diffracting waves and pulses. He is also interested in the study of the scattering from natural surfaces, the GNSS reflectometry, and radar altimeter applications over the land. His activity also regards microwave imaging and objects detection performed through GPR, and the modeling of the radar signature in forward scatter radar systems. Dr. Comite is a Senior Member of URSI. He was a recipient of a number of awards at national and international conferences. Most recently, he received the Young Scientist Award at URSI GASS 2020. He received the Publons Top Peer Reviewers Award for both Geoscience and Engineering, in September 2018, and for Cross-fields in 2019. In 2019 and 2020, he was recognized as an Outstanding Reviewer for the IEEE Transactions on Antennas and Propagation by the IEEE Antennas and Propagation Society. In 2020, he was awarded as the Best Reviewer for the IEEE Journal of Selected Topics in Applied Earth Observations and Remote Sensing. He currently serves as a reviewer for several international journals. He is also an Associate Editor of the IET Journal of Engineering, the IET Microwaves, Antennas and Propagation by the Institution of Engineering and Technology, and IEEE Access.



Pascual D. Hilario Re was born in Murcia, Spain. He received the B.Eng. and the M.Sc. degrees in telecommunications engineering from the Universidad Politcnica de Cartagena, Spain, in 2012 and 2015, respectively. He also received the Ph.D. degree from Heriot-Watt University, Edinburgh, Scotland, UK, in 2019.


His current research interests include retrodirective systems, wireless power transmission applications, automotive radar, and analysis and design of power amplifiers.



George Goussetis (S'99-M'02-SM'12) received the Diploma degree in electrical and computer engineering from the National Technical University of Athens, Greece, in 1998, the B.Sc. degree in physics (Hons.) from University College London, U.K., in 2002, and the Ph.D. degree from the University of Westminster, London, U.K., in 2002. In 1998, he joined Space Engineering, Rome, Italy, as an RF Engineer, and as a Research Assistant with the Wireless Communications Research Group, University of Westminster, U.K., in 1999. From 2002 to 2006,

he was a Senior Research Fellow with Loughborough University, U.K. He was a Lecturer (Assistant Professor) with Heriot-Watt University, Edinburgh, U.K., from 2006 to 2009, and a Reader (Associate Professor) with Queen's University Belfast, U.K., from 2009 to 2013. In 2013, he joined Heriot-Watt, as a Reader, and was promoted to Professor, in 2014.

He has authored or co-authored over 200 peer-reviewed papers five book chapters one book and two patents. His research interests include the modeling and design of microwave filters, frequency-selective surfaces and periodic structures, leaky wave antennas, microwave sensing and curing as well numerical techniques for electromagnetics. Dr. Goussetis has held a research fellowship with the Onassis Foundation in 2001, a research fellowship with the U.K. Royal Academy of Engineering from 2006 to 2011, and a European Marie-Curie experienced researcher fellowship from 2011 to 2012. He was a co-recipient of the 2011 European Space Agency Young Engineer of the Year Prize, the 2011 EuCAP Best Student Paper Prize, the 2012 EuCAP Best Antenna Theory Paper Prize, and the 2016 Bell Labs Prize.



Samantha Griffiths was born in Gloucester, England. She gained her BSc (Hons) in Molecular Biology and Biochemistry from Durham University in 1999, and proceeded to get her PhD in Molecular Virology from University College London in 2003. Her research focussed on the molecular cellular determinants of virus infection and pathogenesis, and current focus includes the detailed study of pathogen-host interactions using high-throughput screening and validation technologies.



Robert J. Chadwick studied Applied Chemistry (MChem) at Northumbria University, Newcastle Upon Tyne (UK). He is currently studying for a PhD in chemistry under the supervision of Prof. Nico Bruns at the University of Strathclyde, Glasgow (UK). He works on biocatalytic polymerisations with a focus on reversible-deactivation radical polymerisations (also known as controlled radical polymerizations) catalysed by metalloproteins.

ORCID iD: 0000-0001-7476-2399



Sumanth K. Pavuluri, B.Tech, MSc, PhD is currently a Post-Doctoral Research Associate with Heriot-Watt University.

Dr. Pavuluri after completing his PhD in 2011 on micro machined antennas. In 2008, he has worked on highly sensitive micro machined microwave sensors for biological and chemical material detection based on waveguides loaded with a frequency selective surface. This work was a finalist in IEEE microwave theory and techniques (MTT) microwave measurement competition 2009. He also worked on Fre-

quency Agile Microwave Oven Bonding System (FAMOBS) from February 2009 to October 2011 and developed patentable new generation open-ended oven prototypes for uniform and efficient curing of the microelectronic chips. This project has reached a technology readiness level of 5. He also worked on commercial automated Remote sensing device for road surfaces in 2012. After working on a Scottish Enterprise high growth spin out project on a patented sensor system product for reducing wastage in the food & drink industries from 2015 to middle of 2017, Dr Pavuluri has successfully spun out a company MicroSense technologies Limited along with Prof. Marc Desmulliez. MicroSense was joint 2016 winner of the Converge Challenge, the Scottish company creation competition and has been commended in 2018 IET (The institution of Engineering and Technology) innovation awards. MicroSense has also featured recently in January 2019 in BBC showcasing a new product development from the company.

In 2017 and 2018, Dr Pavuluri has been a member of Heriot-Watt group in the EPSRC-funded Sonopill project, working on the electronics design and packaging of ingestible medical devices that are for various exploratory sensor systems for integration into capsules.

Dr. Pavuluri's current research interests include medical diagnostics, medical electronics including telemetry and packaging, novel micro fabrication and micromachining methods for RF and acoustic devices for bio medical applications. Other areas of interest are microwave sensing, curing, and integrated circuit packaging.



Chao Guo studied Microbiology (Msc) at the University of Chinese Academy of Sciences, China. He started his PhD project, supervised by Prof. Nico Bruns, at the University of Strathclyde (UK) in 2018. He now works on the engineering of metalloproteins for controlled radical polymerisations.

ORCID iD: 0000-0002-1610-1768



Christine Tait-Burkard, Doctor of Science, Utrecht University Host Factors Involved in the Entry of Coronaviruses into Mammalian Cells Master in Science, ETH Zürich (Switzerland) Bachelor of Science, ETH Zürich (Switzerland)



Jürgen G. Haas is the Head of Infection Medicine and Professor for Viral Genomics at the University of Edinburgh. He is also an honorary NHS consultant Virologist at the Royal Infirmary Edinburgh. After undergraduate studies in Medicine and Biology, he performed postdoctoral trainings at Munich and Harvard University, followed by a medical specialist training in Microbiology at the Universities of Heidelberg and Munich. Before he joined the University of Edinburgh in 2006, he has been Associate Professor at the University of

Munich.

Professor Jürgen Haas' research focuses on the identification and characterization of virus-host interactions that are crucial for the pathogenesis and affect susceptibility and pathogen virulence. Using genome-wide protein interaction and RNA interference screens, his laboratory have identified key events in the viral life cycle for a range of several different viruses including Herpes simplex virus type 1 (HSV-1), Food and Mouth Disease virus (FMDV) and high risk Human Papilloma virus 16 (HPV-16). In HSV-1, we are currently working on cellular factors that affect viral entry and the potential role of HSV-1 in neurodegenerative diseases. In FMDV, we identified host factors that can be exploited for vaccine development and the generation of FMDV-resistant pigs. In HPV, we are investigating a novel cellular tumour suppressor that inhibits E7-mediated oncogenesis. Another current research focus are novel mechanisms of viral inhibition that can be used for antiviral therapy.



Marc P. Y. Desmulliez (SM'87) received the Ph.D. degree in optoelectronics from Heriot-Watt University, in 1995, where he is currently a Professor of microsystems engineering with the Multi-modal Sensing and Micro-Manipulation Research Group. He has coauthored over 470 publications in the fields of microwave engineering, novel manufacturing technologies, and optoelectronics.